**Available Q4 2025**

# JPL Scout 3100

## Wireless DECT Push-to-talk Headset Adapter

**Designed for Critical Communications**

**Designed in the UK, Manufactured in South Korea**

### JPL Scout 3100

The JPL Scout 3100 is a wireless DECT ***push-to-talk*** headset amplifier that is ideal for use where secure, mission critical, conversations are needed, such as public safety dispatch, air-traffic control, radio dispatch operations, and training simulation.

### Overview

| | |
|---|---|
| **Features** | Modern robust design made from toughened plastic to withstand the harshest of conditions |
| | Two charging wells, one for PTT trigger and one for spare battery |
| | Second battery on constant charge - always have a fully charged battery |
| | Push-to-Talk switch with momentary operation |
| | Left and right side belt clip wearing styles |
| | Neatly positioned thumb wheel for receive volume control |
| | Send volume controls positioned on the base station |
| | LED visual indication on trigger for inactive/active microphone |
| | LED visual indication for Power on/off, headset pairing and PTT in-use |
| | DECT Security Step C, Encryption: FIPS-140-2 |
| | Dual PC/analogue connectivity |
| | Range: 400ft (120m) line-of-sight |
| | Battery: 400mAh |
| | Talk time: Wideband- 8hrs, Narrowband - 10hrs |
| | Latency of 15-45ms for narrowband and 45-70ms for wideband |
| | Charge time: 4hrs |

### Specifications

| | |
|---|---|
| **Connection to headset** | Poly compatible QD |
| **Technology** | DECT, 1.88GHz (EU, Rest of World), 1.9GHz (North America) |
| **Base Connection** | Base to desk phone via RJ12- supplied as standard. |
| **Console Interface** | USB, PJ-7 |
| **Certifications** | UKCA, CE, FCC, RoHS |
| **Country of Origin** | Made in South Korea - TAA compliant |
| **Warranty** | 24 Month |
| **Distribution MOQ** | 16 per master carton |
| **EAN** | 5060969682872 |
| **SKU** | 575-406-3100 |



JPL Telecom Ltd, Units 1 & 2, Church Close Business Park, Todber, Sturminster Newton, Dorset DT10 1JH • Tel: +44 (0)1258 820100 • **www.jpltele.com**
JPL Telecom LLC, 445 W Merritt Avenue, Merritt Island, FL 32953, USA • Tel: +1 321-300-1141

**Available Q4 2025**

# JPL Scout 3100

## Wireless DECT Push-to-talk Headset Adapter

### What's Included

| | |
|---|---|
| **Equipment** | 1 x Scout 3100 base station |
| | 1 x Scout 3100 handheld trigger with QD headset connector |
| | 2 x batteries (one for handheld and other as spare) |
| **Ports** | 1 x USB-C port for power |
| | 1 x USB-C port for data-in |
| | 1 x RJ12 port for PJ-7 cable connectivity |
| | 1 x RJ12 port for supervisor interaction |
| **Cables** | 1 x PJ-7 2-prong to RJ12 cable (15ft / 4.5m) |
| | 2 x USB-C to USB-C/A cables (5ft / 1.5m) |
| | 1 x RJ12 to RJ12 Supervisor cable (3ft/1m) |
| | 1 x Multi-country plug with USB-C port |
| **Recommended QD Headsets** | JPL-400, JPL-Icon 100, JPL Connect |

**Hot swappable battery**
Battery can be changed during a live call without dropping the call.




Dual connectivity
Press to select MODE button eg. USB/RJ/PJ-7

Push down to mute button or blank cover for no-mute option

Power On/Off indicator

PC audio indicator

Audio indicator

Headset pairing indicator

Push-to-talk pressed/active

TAA COMPLIANT

**Designed in the UK, Manufactured in South Korea**



JPL Telecom Ltd, Units 1 & 2, Church Close Business Park, Todber, Sturminster Newton, Dorset DT10 1JH • Tel: +44 (0)1258 820100 • **www.jpltele.com**
JPL Telecom LLC, 445 W Merritt Avenue, Merritt Island, FL 32953, USA • Tel: +1 321-300-1141